

Accessories series LQ6



LQ690000

Schrack-Info

- Diode Module: necessary for use for remote switches with central function and the control of different groups
- Capacitor module / compensation module: When using illuminated pushbuttons to control the LQ6 remote switches.

Lamp Type	Power lamp [W]	Current [A]	Capacitor [μF]	max. number of lamps per relay contact at 230V, 50Hz [pcs.]
Incandescent lamps	60	0,27		33
Low-voltage halogen lamps (12 or 24V) with transformer / electronic transformer	20	0,09		55
	50	0,22		22
	75	0,33		14
	100	0,43		11
	150	0,65		7
	200	0,87		5
Fluorescent tubes without compensation or with series compensation	300	1,3		3
	11	0,16	1,3	62
	18	0,37	2,7	27
	24	0,35	2,5	27
	36	0,43	3,4	24
	58	0,67	5,3	15
Fluorescent tubes lead-lag circuit	65	0,67	5,3	14
	85	0,8	5,3	12
	11	0,07		2x 71
	18	0,11		2x 45
	24	0,14		2x 35
	36	0,22		2x 22
Fluorescent tubes with electronic ballast	58	0,35		2x 14
	65	0,35		2x 14
	85	0,47		2x 10
	18	0,09		32
	36	0,16		16
	58	0,25		12
Fluorescent tubes with parallel compensation				
	2x18	0,17		2x16
	2x36	0,32		2x8
	2x58	0,49		2x6
	11	0,16	3	34
	18	0,37	4	26
	24	0,35	4	26
	26	0,43	4	26
	58	0,67	7	14
	65	0,67	7	14
	85	0,8	8	13

DESCRIPTION	AVAILABLE	ORDER NO.
Diodes, 240VAC, 9A		LQ690000
Capacitor module, 240VAC, 1,5μF		LQ690001

